Functional Devices, Inc.
101 Commerce Drive
Sharpsville, IN 46068
Confidence & Peace of Mind in Every Box™

Office: (765) 883-5538 Toll Free: (800) 888-5538 www.functionaldevices.com sales@functionaldevices.com



## **DC POWER SUPPLY**


## **PSH100A24DWB10**

DC Power Supply, 100 VA, 120 to 24 Vac and Switching 120 to 24 Vdc at 2.5 Amp, Metal Enclosure










\* Move internal jumper to "HOT" position if you wish outlets to always be hot otherwise outlets will be switched by main breaker.





## **SPECIFICATIONS**

Transformer	One 100 VA Split-Bobbin
Input Voltage	120 Vac
Frequency	50/60 Hz
Input Wires	Input Power Wires BLK: 120 Vac WHT: Neutral GRN: Ground
Output Wires	DC Supply Output WHT/RED: 24 Vdc WHT/BLU: 24 Vdc COM Auxiliary Output BLU: 120 Vac
	Transformer Output WHT/YEL: 120 Vac WHT/BLU: 24 Vac COM
<b>Over Current Protection</b>	Circuit Breaker
24 Vac ON/OFF	Switch / Breaker (4 Amp)
Main Breaker ON/OFF	Switch / Breaker (10 Amp) Kills power to entire unit: Outlets, Aux. Output, Transformer, and 24 Vdc* Total Combined Output 9A
Dimensions	4.500" H x 8.625" W x 4.500" D
Origin	Made of US and non-US parts

## **NOTE**

This device is not certified for use as a Class 2 power source