


Functional Devices, Inc. 101 Commerce Drive Sharpsville, IN 46068 Confidence & Peace of Mind in Every Box™


www.functionaldevices.com sales@functionaldevices.com Office: (765) 883-5538 Fax: (765) 883-7505 Toll Free: (800) 888-5538

## **CURRENT TRANSFORMER**

## CT-05A0-333

Enclosed Self-Powered Split Core 5 Amp Current Transformer with 333 mV Output







## SPECIFICATIONS

Environment: Indoor Use Only 5 to 176° F (-15 to 80°C) 90% relative humidity Wires: 6', 22 AWG 600V Rated Primary Input (A): 60A max. AC 50/60 Hz Secondary Output (V): 0.333 Vac Accuracy: 0.3% (typical) Linearity: 10%-120% Polarity: White-Hi, Black-Low Frequency Range: 40-400 Hz Max Sense Voltage: 600 Vac Approvals: ETL Listed, CE, RoHS Ratio: 5A/0.333V Alternate ratios available for large orders

