


Functional Devices, Inc. | 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 | Office: (765) 883-5538 | Fax: (765) 883-7505

15 AMP PILOT CONTROL TRACK MOUNT RELAYS


RIBMNU1C

Pilot Relay, 15 Amp SPDT, 10-30 Vac/dc/ 120 Vac Coil. 2.75"Track Mount



RIBMNH1C

Pilot Relay, 15 Amp SPDT, 10-30 Vac/dc/ 208-277 Vac Coil, 2.75" Track Mount













SPECIFICATIONS

Relays & Contact Type: One (1) SPDT Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 20ms

Relay Status: LED On = Activated

Dimensions: 1.70"H x 2.75"W x 0.88"D1/1.38"D2

Housing Detail: See **Housing H** in housing guide for dimensions

Origin: Made of US and non-US parts

Track Mount: 2.750"

MT212 Mounting Track Sold Separately

Approvals: UL Listed, UL916, C-UL, CE, RoHS

UL864, California State Fire Marshal

Gold Flash: Yes Override Switch: No

Contact Ratings:

15 Amp Resistive @ 150 Vac, 28Vdc
15 Amp Inductive @ 150 Vac
10 Amp Resistive @ 120-277 Vac, 28 Vdc
480 VA Pilot Duty @ 240-277 Vac
480 VA Ballast @ 277 Vac
Not rated for Electronic Ballast
600 Watt Tungsten @ 120 Vac (N/C)
240 Watt Tungsten @ 120 Vac (N/C)
1/3 HP @ 120-240 Vac (N/C)

1/6 HP @ 120-240 Vac (N 1/4 HP @ 277 Vac (N/O) 1/8 HP @ 277 Vac (N/C)

Coil Current:

RIBMNH1

33 mA @ 10 Vac 13 mA @ 10 Vdc 35 mA @ 12 Vac 15 mA @ 12 Vdc 46 mA @ 24 Vac 18 mA @ 24 Vdc 55 mA @ 30 Vac 28 mA @ 120 Vac (RIBMNU1C) 39 mA @ 208-277 Vac (RIBMNH1C)

Coil Voltage Input:

10-30 Vac/dc; 120 Vac; 50-60 Hz (RIBMNU1C) 10-30 Vac/dc; 208-277 Vac; 50-60 Hz (RIBMNH1C)

Drop Out = 2.1 Vac / 2.8 Vdc Pull In = 9 Vac / 10 Vdc